

IN ADMIRATION OF MUSIC



DALI ZENSOR Series

MEGALINE EUPHONIA MENTOR

IKON

LEKTOR
► ZENSOR

ZENSOR FAMILY produktblad.indd 1 27/05/11 15.52

DALIZENSOR Series

The new DALI ZENSOR series is a genuine and affordable hi-fi loudspeaker unmistakably based on heritage from DALI's high-end series. And packed with in-house technology, new ideas, and its very own DALI personality.

Consisting of four models, the ZENSOR's cover every need from a compact stereo to an ambitious multi-channel set up. The smallest model includes integrated wall bracket for easy mounting, while both floor standing models are elevated from the floor by aluminium bases to refine acoustics and stability.

Last not least, the visual appearance is an eye pleaser - integrated in a high gloss lacquered front baffle as a natural extension of the sleek cabinet. The ZENSOR design is contemporary, lasting, and stylish.

ZENSOR 1

ZENSOR 1 is the perfect speaker in a compact stereo system, filling small or medium sized rooms with sound. Move it to a larger room, add a subwoofer, and you now have a very capable 2.1 set-up.

ZENSOR 5 & 7

The ZENSOR 5 and especially the ZENSOR 7 will easily fill even large rooms with sound – with or without a subwoofer for assistance in the low frequency area. Obviously the ZENSOR 7 has an authority in the lowest frequency range that makes it the natural choice for very large rooms or for applications where serious low frequency effect is a must.

ZENSOR VOKAL

Because of its clear and ultra intelligible voice reproduction the ZENSOR VOKAL will transform your TV into a hyper detailed mediation system.

DALI offers a wide range of subwoofers to complement a ZENSOR surround set- up and we strongly recommend the new DALI SUB E-12 F for any ZENSOR set-up.







Technical Specifications:

	ZENSOR 1	ZENSOR 5	ZENSOR 7	ZENSOR VOKAL
Frequency Range [+/- 3] dB [Hz]	53 - 26.500	43 - 26.500	40 - 26.500	47 - 26.500
Sensitivity [2.83V/1m] [dB]	86,5	88,0	90,0	88,5
Nominal Impedance [ohms]	6	6	6	6
Maximum SPL [dB]	106	108	110	109
Recommended Amp. Power [Watts]	25 - 100	30 - 150	30 - 150	30 - 120
Crossover Frequencies [Hz]	2.900	2.400	2.400	2.400
Crossover Principle	2-way	2-way	2-way	2-way
High Frequency Driver	25 mm soft dome	25 mm soft dome	25 mm soft dome	25 mm soft dome
Low Frequency/Midrange Driver(s)	1 x 5¼"	2 x 5¼"	2 x 7"	2 x 5¼"
Enclosure Type	Bass reflex	Bass reflex	Bass reflex	Bass reflex
Bass Reflex Tuning Frequency [Hz]	51,5	44,0	40,0	45,0
Connection Input(s)	Single wire	Single wire	Single wire	Single wire
Recommended Placement	Wall/shelf/(Stand)	Floor	Floor	Shelf below TV screen
Magnetic Shielding	Semi shielding	No	No	Semi shielding
Dimensions (H x W x D) [mm]	274 x 162 x 228	825 x 162 x 267	978 x 205 x 312	161 x 441 x 281
Dimensions (H x W x D) [inches]	10.8 x 6.4 x 9.0	32.5 x 6.4 x 10.5	38.5 x 8.1 x 12.3	6.3 x 17.4 x 11.1
Weight [kg/lb]	4,2/9.3	10,3/22.7	14,9/32.8	6,8/15.0

Designed in Denmark | www.dali-speakers.com









ZENSOR FAMILY produktblad.indd 2 27/05/11 15.52